

Apple DuoDisk to Disk][Interface Card

| DB-25 DuoDisk | 20-pin IDC Drive 1 | 20-pin IDC Drive 2 | Function |
|------------------|-----------------------|-----------------------|----------|
|------------------|-----------------------|-----------------------|----------|

| | | | |
|--------------------|---------|----|---------|
| 2, 4, 9, 10 | 1,3,5,7 | | GND |
| 23 | 9 | - | -12 V |
| 7 | 11 | - | +5 V |
| 19 | 13 | - | +12 V |
| 20 | 15 | - | +12 V |
| 15 → 00 | 2 | - | PH0 |
| 16 → 01 | 4 | - | PH1 |
| 17 → 02 | 6 | - | PH2 |
| 18 → 03 | 8 | - | PH3 |
| 5 | 10 | - | /WREQ |
| 12 | 20 | - | WRPROT |
| 3 | 16 | - | RD |
| 6 | 18 | - | WR |
| 11 → ENBL A | 14 | - | /DRIVE1 |
| 8 → ENBL B | - | 14 | /DRIVE2 |
| 24 | 12 | - | SEL |